



12526 E. Jamison Place, Suite 100 • Englewood, Colorado 80112 • (303) 925-1133 • Fax: (303) 790-9540

1-800-683-1229 • e-mail: info@rmpc.com

MULTIQUIP GENERATOR PERFORMANCE DATA

Model	Standby Output KW (KVA)	Prime Output KW (KVA)	Generator RPM	Frequency	Sound Level dB(A) Full load 23 feet	Amps				Voltage		Voltage Regulation No load to full load	Power Factor
						Single Phase 120 V	Single Phase 240 V	Three Phase 240 V	Three Phase 480 V	Single Phase	Three Phase		
DA7000SS	7 KW	6 KW	3600	60 Hz	65.7	29.2A (2 sets)	29.2A	-	-	120/240	-	+/-3%	1.0
DCA25SS	22 KW (27 KVA)	20 KW (25 KVA)	1800	60 Hz	65	55.5A (4 wire) 60Ax2 (zigzag)	27.8 (4 wire) 60A (zigzag)	60A	30A	120, 127, 139, 240, 254, 277V Switchable	208, 220, 240, 416, 440, 480V Switchable	+/-1%	0.8
DCA45SS	37 KW (47 KVA)	36 KW (45 KVA)	1800	60 Hz	64	100A (4 wire) 108Ax2 (zigzag)	50A (4 wire) 108A (zigzag)	108A	54A	120, 127, 139, 240, 254, 277V Switchable	208, 220, 240, 416, 440, 480V Switchable	+/-1.5%	0.8
DCA70SS	61 KW (77 KVA)	56 KW (70 KVA)	1800	60 Hz	65	155.5A (4 wire) 168Ax2 (zigzag)	77.8A (4 wire) 168A (zigzag)	168A	84A	120, 127, 139, 240, 254, 277V Switchable	208, 220, 240, 416, 440, 480V Switchable	+/-1.5%	0.8
DCA70US	62 KW (77 KVA)	56 KW (70 KVA)	1800	60 Hz	60	155.5A (4 wire) 168Ax2 (zigzag)	77.8A (4 wire) 168A (zigzag)	168A	84A	120, 127, 139, 240, 254, 277V Switchable	208, 220, 240, 416, 440, 480V Switchable	+/-0.5%	0.8
DCA100SS	88 KW (110 KVA)	80 KW (100 KVA)	1800	60 Hz	67	222.2A (4 wire) 241Ax2 (zigzag)	111.1A (4 wire) 241A (zigzag)	241A	120A	120, 127, 139, 240, 254, 277V Switchable	208, 220, 240, 416, 440, 480V Switchable	+/-1.5%	0.8
DCA125SS	110KW (137 KVA)	100 KW (125 KVA)	1800	60 Hz	67	277.8A (4 wire) 301Ax2 (zigzag)	138.9A (4 wire) 301A (zigzag)	108A	150A	120, 127, 139, 240, 254, 277V Switchable	208, 220, 240, 416, 440, 480V Switchable	+/-1.5%	0.8
DCA220SS	194 KW (242 KVA)	176 KW (220 KVA)	1800	60 Hz	66	888.9A (4 wire)	444.4A (4 wire)	962A	481A	120, 127, 139, 240, 254, 277 Adjustable	208, 220, 240, 416, 440, 480 Reconnectable	+/-1.5%	0.8